



PRO X PRO
PRO X
PRO X PRO
PRO X



E·SERIES SMART REPAIR KIT

for professionals, by experts.



E-SERIES SMART REPAIR KIT

The PRO X Smart Repair tool offers the very latest in brushless motor technology. The 12V cordless battery is lightweight and portable for ease of use throughout in any working environment. The quick change system enables effortless switching between rotary and random orbital action for both sanding and polishing applications. Housed in a durable kit box with a full range of pads and adaptors (the battery charger is not included).



*E-SERIES PRO XC Charger sold separately

Part number	610312	610329	610336
Plug type	EU	UK	USA
Weight	2 lbs		
Input voltage	220 V / 240 V		120 V
Charge current	9 A		
Wall mounting possible	Yes		
Loading progress display	Yes		

Compatible with PRO XB 12 V

Features & Benefits

- Multi purpose machine → Ideal for spot sanding and polishing
- Cordless tool → Lightweight and portable
- Brushless motor → High power and low maintenance
- Soft rubber ergonomic design → Maximum comfort
- Low vibration → Optimal balance and user comfort
- Quick change system → Alternate from rotary to random action
- Clear RPM range → Identify suitable speed
- LED speed indicator → Displays different working levels

Part number	610305	612712
Market certification	EU / UK	USA
Battery voltage	12 V	
Battery capacity	2.5 Ah	
Max. backing pad size	3"	
Orbit	1/8" - 1/2"	
No-load speed	400-2000/-3000/-4000/-5800 rpm	
Orbit rate, no load	800-4000/-6000/-8000/-11600 opm	
Kit size (W x L x H)	14" x 17.5" x 6"	
Tool size (W x L x H)	10" x 2.5" x 3.75"	
Kit weight	5.5 lbs	
Tool weight	1.3 lbs	

Included

- 1 Smart rotary adapter
- 1 Smart random orbital adapter 1/8" stroke
- 1 Smart random orbital adapter 1/2" stroke
- 1 Smart adhesive pad 1"
- 1 Smart grip pad 1"
- 1 Smart grip pad 3"
- 2 Batteries E-SERIES PRO XB 12 V



INDASA USA
salesusa@indasausa.com
www.indasa-abrasives.com

